

Архангельск (8182)63-90-72
 Астана (7172)727-132
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89
 Иваново (4932)77-34-06

Ижевск (3412)26-03-58
 Иркутск (395)279-98-46
 Казань (843)206-01-48
 Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Липецк (4742)52-20-81
 Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81
 Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16
 Россия (495)268-04-70

Пермь (342)205-81-47
 Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54
 Сочи (862)225-72-31
 Ставрополь (8652)20-65-13
 Казахстан (772)734-952-31

Сургут (3462)77-98-35
 Тверь (4822)63-31-35
 Томск (3822)98-41-53
 Тула (4872)74-02-29
 Тюмень (3452)66-21-18
 Ульяновск (8422)24-23-59
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Ярославль (4852)69-52-93

<https://inficon.nt-rt.ru> || inb@nt-rt.ru

Детектор формовочного газа AST100FG

FORMING GAS LEAK DETECTOR

Forming gas (95% nitrogen/5% hydrogen), an inexpensive and readily available gas, can be used to leak check an empty AC system using AST100FG. This saves money and reduces environmental impact compared to leak checking with refrigerant. AST100FG is also intrinsically safe for use in other applications where flammable or explosive gases are present.



ADVANTAGES

- Detects forming and combustible gases
- Easy to use
- Long sensor life
- Intrinsically safe
- Includes UV inspection light
- Runs on two D-cell batteries

TYPICAL APPLICATIONS

- Automotive AC service with forming gas
- Propane forklift leaks
- Hydrogen fuel cell leaks
- Fuel system leaks for gasoline or LNG vehicles

Includes	Combustible gas sensor Two D-size alkaline batteries Carrying case UV Inspection light
Detects	Hydrogen forming gas Gasoline Natural gas Propane Butane and more
Sensitivity	Forming gas: 7g (0.25 oz.)/year R134a equivalent 5 ppm for methane, propane, isobutane, and hydrogen 1 ppm for gasoline
Power source	Two D-size alkaline batteries (use Duracell® MN1300 to maintain intrinsically safe approval)
Battery Life	25 hours
Weight	1.54 lb. (700 g)
Certifications	CE Intrinsically safe for Class I, Division I, Groups A - D, T4 and II 3G Ex nA nL IIC T4 X as per MET Laboratories Listing #E112145
Probe length	15 in. (38 cm)
Warranty	Three-year

AST100FG	AST100FG
Accessories and Replacement Parts	
Sensor	706-700-G1